

PROGRAMMING THE Z80

EX AF, AF' Exchange accumulator and flags with alternate registers.


Function: AF ↔ AF'

Format:

0	0	0	0	1	0	0	0
---	---	---	---	---	---	---	---


 08

Description: The contents of the accumulator and status register are exchanged with the contents of the alternate accumulator and status register.



Timing: 1 M cycle; 4 T states; 2 usec @ 2 MHz

Addressing Mode: Implicit.



Example: EX AF, AF'

Before:

After:

